Wire identification chart

*Note that the identification comes from the uphill component.

Wire identification exemple: 12 - A47J1.8 - 16

Voltage		Circuit number	Wire size
0			0000
5	Ground circuits:		000
0/12	Electronic = Use I/O module number followed by an "R" and pin number. (ex: A47RJ1.8, A54RJ2.14)		00
0/24	Electronic ground studs = Use number "00" followed with the stud location and sequential number. (ex: 00R1, 00F4)		0
12	Chassis = Use number "0" followed by the ground stud location and sequential number. (ex: 0EV1, 0FH2)		1
24			2
120	Power and voltage carrying circuits:		3
ANA	Power distribution = Use uphill component identification as circuit name. (ex: F96, CB22)		4
BBUS	Multiplex outputs = Use output module number and pin number as circuit name. (ex: A55J1.4, A49J2.9)		6
DATA	Relays, diodes, resistors and any other component outputs =		8
DBUS		Use component name and pin number as circuit name. (ex: Sw55.A, R30.87, D12.B)	10
J1587	Networks:		12
J1939	DL0 = Bbus mux	DL7 = Engine subnet	14
J2284	DL1 = J1939	DL9 = Power train subnet	16
LIN	DL2 = J2284	900 / 901 = J1587	18
PWM	DL3 = Dbus mux		20
GND			22
OTHER			24

PREVOST	WIRING DIAGRAM	Na	REMISION
FRE VUS 1	MIKING DIAGRAM	NO: D061780 Page M 1/1	1